

Development of Automotive Alternator Test Bench

**Zetty Rohaiza Binti Mohd Sahak^{1*}, Ahmad Fakaruddin Bin Mohd Fauzi¹,
Muhammad Faiz Bin Abdullah¹**

Politeknik Sultan Salahuddin Abdul Aziz Shah Selangor, Malaysia

***Corresponding author E-mail:** zetty.rohaiza@psa.edu.my

Abstract

An automotive alternator converts mechanical energy into electrical energy to power a vehicle's electrical components and charge the battery. A car's electrical system's functionality is heavily reliant on the operational integrity of both the alternator and battery. During alternator maintenance, a mechanic must remove the alternator from the confined engine bay, inspect it, clean or replace internal components, re-install it, and then conduct a test. The mechanic needs to redo all the process if the alternator is still not operating properly. The time period of this maintenance process could be lengthy due to complexity of the work. Thus, the new test bench aims to simplify alternator servicing by allowing for off-vehicle testing, reducing maintenance time and cost. The test bench uses an electric motor to simulate engine rotation, driving the alternator in between 1500 rpm to 2000 rpm and allowing for voltage output measurement to diagnose potential issues. This avoids repeated removal and installation of the alternator during troubleshooting. A properly functioning alternator is expected to deliver an output voltage range between 13.5 V to 14.5 V. A voltage reading below than this range suggests a charging issue, and the alternator should be removed from the test bench for necessary servicing. This product allows mechanics to repeatedly test the alternator without reinstalling it in the engine bay, saving time until the issue is resolved.

Keywords: *Alternator Servicing, Test Bench, Maintenance Time.*

1. Introduction

Alternator test bench is a device designed to evaluate the voltage and amperage output of an alternator. In automotive industry, the alternator test bench is very useful to ease the alternator maintenance process. The current method consists of testing and analyzing the performance of alternator at various speed conditions (Tharani et al., 2016). Various types of alternator tester machines are available in the market, capable of testing the voltage but the price is expensive. It could reach as high as RM10,000 – RM30,000 per unit depending on model and technology.

As a result of misdiagnosis, the alternator is among the most frequently returned repair components. Bench testing an alternator on a test stand is essential to ensure its output falls within specified parameters. Normal working alternator usually gives reading in between 13.5 to 14.5 V. Readings outside this range may indicate problems with the alternator.

1.1 Problem Statement

As one of a primary component of any automotive vehicle, alternators should be checked by using a test bench. The process of maintaining the faulty alternator is where the mechanic has to remove the alternator from engine bay, repair the alternator and install back on its original place. The problems faced by every mechanics after completing the maintenance work is to assess the alternator's functionality and health status. The duration of this work could be long and challenging depending on types of alternator damage involved. It may take 1-2 hours or more.

Typical alternator issues include brush degradation, regulator relay malfunction, bearing seizure, stator winding failure, and diode bridge defects. Mechanics often rely on their experience or sometimes educated guesses to diagnose and fix issues before reinstalling the alternator in the vehicle for testing. Should the alternator fail to perform as intended, the diagnostic and repair procedure is repeated, as previously outlined.

1.2 Objective

The main objectives of this research are as follows:

- i. To develop an automotive alternator test bench.
- ii. To aid the servicing and installation tasks performed by mechanic.
- iii. To reduce the cost of tool ownership and maintenance work.

1.3 Scope

The scopes of this research are divided into 3 criteria's:

- i. The system should be capable of testing an ideal output voltage of 14 volts.
- ii. It must support alternators with current ratings ranging from approximately 70 to 150 amps.
- iii. The test bench design is compact and space-efficient, making it suitable for small workshops specializing in passenger vehicle alternator testing.

2. Literature Review

An alternator is a device that functions as an electrical generator, converting mechanical energy derived from the engine's rotation into electrical energy in the form of alternating current. The main parts of alternator consist of rotor, stator, rectifier, voltage regulator, brush assembly and slip ring. Most alternators utilize a rotating electromagnetic field combined with a stationary armature.

In a vehicle, the battery and alternator work together to power the electrical system. The battery initiates the engine start, while the alternator takes over to power electrical components such as headlights, radio and panel instruments and recharge the battery while the engine is running. The battery voltage typically increases from 12.6V to 13.5-14.5V during the charging process.

The engine's crankshaft rotation transmits mechanical power via a drive belt to a pulley mounted on the rotor shaft. As the rotor spins, its embedded magnetic field rotates within the stationary stator windings, inducing an alternating current (AC) through electromagnetic induction. This AC output is then converted into direct current (DC) by a rectifier assembly comprising multiple diodes, ensuring a stable DC supply for the vehicle's electrical system.


Alternator is subject to mechanical, electrical and magnetic losses because of involvement of energy transformation (Adamiec et al.,2018). Various tests can be performed to measure the operational efficiency in actual operating conditions or on a test bench (Whaley et al.,2004). Voltage regulator testing can be performed by revving the engine to 2000 rpm and monitoring the alternator output voltage. Any rises above 15V or less than 12.5V may indicates a regulator's problem. (Weibin et al.,2014). Part load and full load tests are conducted. Various parameters such as speed, voltage and current are under various testing conditions by using components like PLC, SCADA, profibus and servo drive (Tharani et al.,2016).

There are numerous types of alternator test benches available on the market, featuring a wide range of designs and price points. Over time, these test benches have evolved to enhance user convenience and simplify the diagnostic and maintenance process. Table 1 shows comparison between three different test benches.

Table 1: Existing product comparison

Product Types	Feature
 Type A	• Features: Designed for testing the latest generation computerized starters and "smart" alternators with COM, BSS, LIN, and RVC - PWM control signals. • Advantages: Offers enhanced operator safety with a work area cover, automatic alternator belt tensioning, and adjustable tooling fixtures for quick mounting.
 Type B	• Features: Equipped with a 2.2kW single-phase motor and digital ammeter and voltmeter for precise measurements. • Advantages: Supports 12V and 24V testing with switchable load increments and includes built-in rectifier and regulator testers.
 Type C	• Features: Allows testing of 12/24V alternators and voltage regulators under load, with real-time oscillogram displays for comprehensive diagnostics. • Advantages: User-friendly interface requiring minimal operator training, suitable for a wide range of alternator types.

3. Methodology

**Figure 1:** Methodology Flow Chart

Development concept A, illustrated in Figure 2, incorporates an adjustable rheostat set to 14 V, with the rotor capable of spinning up to 1000 rpm. When the alternator operates at this voltage level, the recoil current can be measured. This current represents the electromagnetic response generated by the alternator's rotor as it spins within the stator windings. A recoil

current above 44 A indicates that the alternator's internal components, such as the rotor windings and brushes, are in good condition, allowing it to generate sufficient magnetic flux for proper operation. Conversely, a recoil current below this threshold may suggest issues like worn brushes, damaged windings, or poor electrical connections, which can impair the alternator's performance and charging capability. Thus, measuring the recoil current provides a valuable diagnostic indicator for assessing alternator health without requiring full operational load testing.




Figure 2: Development Concept A

Development concept B illustrated in Figure 4, employs a straightforward approach utilizing a hand drill to spin the alternator and a multimeter to measure the output voltage. While this method is simple and cost-effective, its practicality and safety are questionable due to several factors. Firstly, the hand drill provides inconsistent rotational speeds, making it difficult to maintain the alternator within the optimal testing range (typically 1500–2000 rpm). This variability can lead to unreliable voltage readings and inaccurate diagnostics. Secondly, the manual operation increases the risk of mechanical hazards such as slippage, sudden acceleration, or loss of control, which could result in injury or damage to the alternator and surrounding equipment. Additionally, the absence of proper mounting or shielding exposes the operator to moving parts and electrical components, further compromising safety. To improve this concept, incorporating a motorized drive with speed control and secure mounting fixtures would provide more stable and repeatable testing conditions. Adding protective covers and safety interlocks would enhance operator safety, making the testing process both more reliable and safer.




Figure 3: Development Concept B

Development concept C illustrated in Figure 3, comprises a motor capable of rotating up to 2500 rpm, a drive belt, and a power source supplied either by a battery or a 3-pin plug. Once the alternator reaches a rotational speed between 1500 and 2000 rpm, the output voltage and current can be measured. For a healthy alternator, the voltage output should fall within the range of 13.5 to 14.5 volts. This design offers several advantages over simpler test setups. The higher rotational speed capability (up to 2500 rpm) allows the alternator to be tested across a broader operational range, closely simulating real engine conditions. Using an electric motor as a drive source provides consistent and controllable speed, improving the accuracy of the

voltage and current measurements. Furthermore, the inclusion of a belt drive ensures mechanical isolation between the motor and alternator, reducing vibration and wear on components. The flexibility of power supply options (battery or 3-pin plug) enhances the portability and usability of the test bench in various workshop environments. Compared to designs limited to lower rotor speeds or static voltage application (such as those relying solely on rheostats), this concept enables dynamic testing under realistic load and speed conditions. This facilitates more reliable diagnostics and helps identify issues like voltage regulation faults, winding defects, and bearing problems with greater precision.




Figure 4: Development Concept C

Table 2 indicates that Design C is the most suitable design, as it offers greater advantages compared to Design A and B. Design C demonstrate superior practicality and gives good durability among the three alternatives, making it the optimal choice for reliable and efficient alternator testing.

Table 2: Selection process for concept design

	Design A	Design B	Design C
Durability	X	X	✓
Practicality	X	X	✓
Cost	X	✓	X
Size	✓	✓	X
Power Output	X	X	✓
Maintenance	✓	X	✓
Total	2/6	2/6	4/6

After selecting the third concept design as a final product design, detailed drawings were developed as shown in Figure 5. Overall measurement of the test bench is 110cm(L) x 40cm(W) x 36cm(H).




Figure 5: Detail design

The frame is constructed from mild steel with a powder-coated finish to ensure durability and resistance to corrosion in workshop environments. The pulleys are manufactured from high-strength aluminium alloy to balance weight reduction and mechanical robustness. The belt used is a reinforced V-belt designed to withstand repeated stress and maintain grip during operation. The angle of contact between the pulley and belt is optimized at approximately 150 degrees to maximize friction and minimize slippage. Assembly instructions specify the use of precision-aligned bearings and tensioning mechanisms to facilitate easy adjustment of belt tension, ensuring consistent performance across varying loads.


The main project components consist of steel base stand, motor, panel board, alternator, bench bracket and drive belt as shown in Figure 6. The assembly and fabrication process were done at welding workshop. After completion of the fabrication, a series of testing have been carried out in order to determine the functionality of the bench and make a necessary modification.



Figure 6: Main parts of alternator test bench

4. Result & Discussion

Figure 7 shows an operating procedure of the test bench. Firstly, the malfunction alternator has to be removed from engine bay. Then, the alternator needs to be installed at the test bench bracket. After that, belt installation with proper tension. Adjustment of the belt tension can be made through bolt slot. To test the function of the alternator, electric motor (represents the engine) will drive the alternator at 1500 to 2000 rpm via belt. At this speed, good alternator will show an output voltage of 13.5 to 14.5 V at the panel. With the reading, mechanic is able to identify the types of alternator problems to be solved. If the voltage reading is low (12.5 V or lower), it indicates charging problem and mechanic could remove it from the tester bench and do appropriate maintenance work. After the problem has been rectify, the alternator can be reinstalled back at the engine bay.






Figure 7: Operating procedure of alternator test bench

Maintenance time for manual method

Currently, mechanics at Bateriku Sdn. Bhd. workshop used manual method to do a maintenance work. An alternator replacement normally will take about 1-2 hours depending on model and location of the alternator at engine bay. To remove the alternator, drive belt has to be taken out, disconnect the wire and unbolted it from the bracket. Installation process will follow the reverse sequence. Some vehicles have a high mounted alternator which would be easy to access. However, in some other models, underbody panels and components need to be removed to have an access to the alternator.

Sample testing

Five different samples of alternator have been tested which consists of 4 faulty and 1 good alternator. The purpose of using good alternator for testing is to get the base time of removal and installation at the engine bay without doing the repair work.

Selected mechanics with similar competency were performing the maintenance work of two different methods. Mechanic A, by using test bench and Mechanic B, by using manual method. Same alternators (5 units) have been used for those two methods. Table 3 and Table 4 shows the test result for Mechanic A and B respectively. Removal, troubleshoot, installation and total time have been recorded to evaluate the difference between test bench and manual method.

Table 3: Testing result of Mechanic A by using test bench method

Alternator sample	Removal time (t_1 , min)	Troubleshoot time (t_2 , min)	Installation time (t_3 , min)	Total time (T , min)	Voltage reading (volt)	Types of faulty	No. of repetitive work
No. 1	35	0	42	77	14.3	None	0
No. 2	40	35	42	117	12.5	Worn brush	1
No. 3	38	80	40	158	15.2	Regulator failure	3
No. 4	43	60	38	141	10.5	Stator winding burnout	2
No. 5	47	30	48	125	11.6	Worn bearing	1
Average	40.6	41	42	123.6	—	—	—

Table 4: Testing result of Mechanic B by using manual method

Alternator sample	Removal time (t ₁ , min)	Troubleshoot time (t ₂ , min)	Installation time (t ₃ , min)	Total time (T, min)	Voltage reading (volt)	Types of faulty	No. of repetitive work
No. 1	39	0	40	79	14.3	None	0
No. 2	42	36	42	120	12.5	Worn brush	1
No. 3	96	82	108	286	15.2	Regulator failure	2
No. 4	98	59	102	259	10.5	Stator winding burnout	2
No. 5	47	28	48	123	11.6	Worn bearing	1
Average	64.4	41	68	173.4	—	—	—

From Table 3, the base time for alternator replacement (sample number 1) without any troubleshooting work is 77 minutes. This is normal work time for Mechanic A. From Table 4, base time for alternator replacement without any troubleshooting work is 79 minutes. This is normal time for Mechanic B.

The other four samples have a different type of faulty with some amount of repetitive work due to incorrect faulty prediction of alternator problem. This will increase total work time. However, test bench method is able to reduce the removal and installation time because the mechanic can skip the work process at engine bay. It is significantly may shorten the total time, T. For example, sample number 3 have the longest total time (158 minutes) because mechanic required three times of repetitive work to identify the true issue which is voltage regulator failure. Nevertheless, it is still consuming less time compare to manual method as shown in Table 4. Although Mechanic B required two times of repetitive work to solve the problems for alternator number 3, total time is higher (286 minutes). Removal and installation process at engine compartment obviously contribute to the increased amount of time.

The other result also supports the evidence as shown at the alternator number 4. Both Mechanic A and B required two times of repetitive work with total time of 141 minutes and 259 minutes respectively to identify the stator winding burnout and complete the whole process. The time difference between both mechanics is 118 minutes.

The average total time for Mechanic A is 123.6 minutes compare to average total time for Mechanic B with 173.4 minutes. This gives a difference of 49.8 minutes between test bench and manual method. It clearly shows that, by using alternator test bench, it may save time by 28.7% and hence save the labour cost.

Cost

Total parts and manufacturing cost for this project is RM1,200 compare to current market test bench price which is between RM10,000 to RM30,000. Although, the function of alternator test bench in the market is more but for the purpose of Bateriku Sdn. Bhd. workshop usage it is just enough.

5. Conclusion

The study explored the feasibility of developing an alternator test bench to assist with alternator maintenance. The result proves that average total work time could be reduced by 33%. Mechanics are able to skip the installation and removal time on the engine bay during troubleshooting process which is very helpful. Less time means cost reduction in terms of labour. High cost of ownership with the purchase of test bench in the market may also be avoided. As a conclusion, the study has fulfilled the objectives stated which are to develop an alternator test bench, to aid the servicing and installation tasks performed by mechanic and to reduce the cost of tool ownership and maintenance work.

References

- Adamiec, M., Dziubinski, M., & Siemionek, E. (2018). Research of the alternator on the stand – efficiency aspect. *International Automotive Conference IOP Conf., Series: Materials Science and Engineering* 421 (2018) 022001.
- Evangelista, R. D. (2022). 24-Wolts Automotive Charging System Trainer and Tester Bench. *United International Journal for Research & Technology*, Volume 03, Issue 06.
- Neethashree, N.R., Yogesha, B., & Kumar, G. P. (2013). Automation of Alternator Test Bench to Ensure Accurate Testing Using PLC and HMI. *International Journal of Engineering Research & Technology (IJERT)*, Volume 2 Issue 7.
- Tharani, E., Karthikeyan, V., Dharanith, S., & Divya, S. (2016). Alternator Performance Testing Using PLC and SCADA. *International Journal of Innovative Research in Electrical, Electronics, Instrumentation and Control Engineering*, Volume 4 Issue 5.
- Weibin, W., Yue, F., Junyi, D., Pengbo, X., Yunlin, F., Tiansheng, H., Jiewei, C., & Luoshi, L. (2014). Integrated Durability of Automobile Alternator Test System Design Based on LabVIEW. *The Open Mechanical Engineering Journal*, 8, 839-845.
- Whaley, D.M., Soong, W.L., & Ertugrul, N. (2004). *Australasian Universities Power Engineering Conference (Brisbane)*.